

# **TR-54D**


## **Transceiver Module**

### **Data Sheet**



## Description

TR-54D is a family of IQRF transceiver modules operating in the 868 MHz and 916 MHz license free ISM (Industry, Scientific and Medical) frequency band. Its highly integrated ready-to-use design requires no external components. Extra low power consumption fits for battery powered applications. SMT mounting and small dimensions allow space saving.




## Applications

- Telemetry
- Building automation
- Control & regulation
- Remote data acquisition
- Communication links
- Wireless networks
- RF connectivity in many other areas

## Key features

- Complete solution with operating system, easy to use
- FSK modulation
- Selectable band 868 / 916 MHz, multiple channel
- Selectable RF bit rate
- MCU with extended resources
- Extra low power consumption, power management modes
- SPI interface supported by OS on background
- 18 pins, 1 I/Os, 1 input, 4 A/D inputs
- Stamp hole pads, SMT mounting, no SIM card compatible
- Serial EEPROM
- Small dimensions

## Simplified schematics



## Electrical specifications

(Typical values unless otherwise stated, for brief guidance only)

Supply voltage ( $V_{CC}$ ) <sup>1</sup>	2.2 V min., 3.4 V max., <b>3.0 V typ.</b> , stabilized.
Operating temperature	0 °C to +70 °C -40 °C to +85 °C (Industrial) available on request
Supply current	
Sleep mode	380 nA (if all peripherals including MRF49XA disabled <sup>4</sup> )
Additional supply current	800 nA (if watchdog enabled) 7.5 µA (if brown-out detection enabled)
Run mode	1 mA (MRF49XA disabled)
Additional supply current	0.6 mA (MRF49XA on)
Rx mode	13 mA (STD mode) 400 µA (LP mode <sup>5</sup> ) 35 µA (XLP mode <sup>5</sup> )
Tx mode	14 mA – 24 mA (according to RF output power)
RF sensitivity <sup>2</sup>	-110 dBm @ 868 MHz, 1.2 kb/s - 99 dBm @ 868 MHz, 19.2 kb/s -109 dBm @ 916 MHz, 1.2 kb/s -102 dBm @ 916 MHz, 19.2 kb/s
RF output power	Up to 5 dBm, programmable in 8 steps (7 – 0), -3dBm/step
RF range (TR-52DA) <sup>3</sup>	Up to 850 m @ 1.2 kb/s Up to 650 m @ 19.2 kb/s
Nominal frequency	868.35 MHz or 916.50 MHz (software selectable)
Channels	See IQRF OS User's guide, Appendix 2, Channel maps
RF data modulation	FSK (frequency-shift keying)
RF data transmission bit rate	1.2 kb/s, 19.2 kb/s, 57.6 kb/s, 86.2 kb/s
Input voltage on Q4 to Q15 pins	0 V to $V_{CC}$
A/D converter	10 b, 4 inputs (multiplexed S&H, successive approximation)
Input A/D impedance	10 kΩ max.
Dimensions	20.2 mm x 14.9 mm x 3.0 mm (TR-54D) 26.4 mm x 14.9 mm x 3.0 mm (TR-54DA)

**Note 1:** RF power and other parameters depend on supply voltage. Refer to datasheets of MCU and RF IC used. Test your application with respect to required supply voltage range.

**Note 2:** RF sensitivity depends on frequency band and bit rate.

**Note 3:** RF range strongly depends on module orientation and surroundings.

**Note 4:** Additional current is consumed when a peripheral is enabled.

**Note 5:** Depends on interferences.

Users have to ensure observing local provisions and restrictions relating to the use of short range devices by software, e.g. the CEPT ERC/REC 70-03 Recommendation and subsequent amendments in EU.

## Absolute maximum ratings

Stresses above those values may cause permanent damage to the device. Exposure to maximum rating conditions for extended periods may affect device reliability.


Supply voltage ( $V_{CC}$ )	4 V
Voltage on Q4 to Q15 pins	-0.3 V to ( $V_{CC} + 0.3$ V)
Storage temperature	-50 °C to +100 °C
Ambient temperature under bias	-40 °C to +85 °C

## Basic parts

Part	Type	Manufacturer	Note
MCU	PIC16LF1938-I/ML	Microchip	
RF IC	MRF49XA	Microchip	
EEPROM	24AA16/MC	Microchip	2 kB

For more information refer to respective datasheets.

Pin	Name	Description
Q1 <sup>6</sup>	<b>GND</b>	Ground
Q2	<b>GND</b>	Ground
Q3	<b>VCC</b>	Power supply voltage
Q4	<b>IO/TX</b> RC6 TX	General I/O pin UART TX
Q5	<b>IO/RX</b> RC7 RX	General I/O pin UART RX
Q6	<b>IO/SCK/SCL</b> RC3 SCK SCL	General I/O pin SPI clock input I <sup>2</sup> C clock
Q7	<b>IO/SDI/SDA</b> RC4 SDI SDA	General I/O pin SPI data I <sup>2</sup> C data
Q8 <sup>7</sup>	<b>IO/SDO</b> RC5 SDO	General I/O pin SPI data out
Q9	<b>IO/LED1</b> RB7 LED1	General I/O pin LEDR supported by OS
Q10	<b>IO/AN/LED2</b> RA2 AN2 LED2	General I/O pin Analog A/D input LEDR supported by OS
Q11	<b>IO/AN/-SS</b> RA5 AN4 -SS	General I/O pin, Analog A/D input SPI Slave select
Q12	<b>IO/AN</b> RB4 AN11	General I/O pin Analog A/D input
Q13	<b>I</b> RE3	General input only pin
Q14	<b>IO/AN</b> RA0 AN0	General I/O pin Analog A/D input
Q15	<b>IO</b> RC2	General I/O pin
Q16		Do not use, leave unconnected
Q17 <sup>6</sup>	<b>GND</b>	Ground
Q18 <sup>6</sup>	<b>ANT</b>	Antenna




**Note 6:** Not implemented for TR-54DAx.


**Note 7:** This pin is used as output during initial ~250 ms boot-up to recognize programming mode.

There are no on-board protection series resistors on I/O pins. It is recommended to use series resistors 200 Ω on each pin used to protect against collisions due to possible failures in HW or SW.


**Figure 1:** Relative RF range vs. level for the `setTXpower(level)` function. Refer to IQRF OS Reference guide.




**Figure 2:** Relative RF range vs. level for the `checkRF(level)` detection. Refer to IQRF OS Reference guide.



**Figure 3:** Relative decrease of RF input signal vs. antenna edge spacing to conductive areas




Conductive areas close to the antenna must be avoided.  
Recommended minimal spacing is 10 mm.


**Figure 4:** Relative RF range vs. antenna orientation (radiation patterns)

## Dimensions


TR-54D



TR-54DA



## Recommended PCB layout



Top view, units: mm





---

# Sales and Service

---

## Corporate office

MICRORISC s.r.o., Delnicka 222, 506 01 Jicin, Czech Republic, EU  
Tel: +420 493 538 125, Fax: +420 493 538 126, [www.microrisc.com](http://www.microrisc.com)

## Partners and distribution

Please visit [www.iqrf.org/partners](http://www.iqrf.org/partners)

---

## Quality management

*ISO 9001 : 2009 certified*

*Complies with ETSI directives EN 30279 V.1.2.1:99, ETS 30683:97, ETSI EN 301489-1:00,  
ETSI EN 300220-1:00, ETSI EN 300390-2V.1.1.1:00*

*Complies with FCC directives FCC CFR, Title 47, Part 15, Section 15.209, FCC CFR, Title 47, Part 15, Section 15.249*

*Complies with Directive 2002/95/EC (RoHS)*



## Trademarks

*The IQRF name and logo are registered trademarks of MICRORISC s.r.o.  
PIC, SPI, Microchip, RFM and all other trademarks mentioned herein are property of their respective owners.*

## Legal

*All information contained in this publication is intended through suggestion only and may be superseded by updates without prior notice. No representation or warranty is given and no liability is assumed by MICRORISC s.r.o. with respect to the accuracy or use of such information.*

*Without written permission it is not allowed to copy or reproduce this information, even partially.*

*No licenses are conveyed, implicitly or otherwise, under any intellectual property rights.*

*The IQRF products utilize several patents (CZ, EU, US)*

---

**On-line support: [support@iqrf.org](mailto:support@iqrf.org)**

---



Smarter wireless. Simply.